



# AUTOMATIC TRANSFER SWITCHES

## UNITED STATES

### SPECIFICATIONS

TRANSFER SWITCHES															
<b>Model Number</b>	071210	071250	071270	071212	071211	071251	071271	071071	071070	071068	071057	071094	071095	071055	01918
<b>Frequency (Hz)</b>	60														
<b>Voltage (VAC)</b>	120/240														
<b>Amps (A)</b>	100	150	200	100	150	200	100	150	200	2 X 200	200	100	50		
<b>Phase</b>	Single														
<b>Poles</b>	2														
<b>Controller Type</b>	TRCM							Symphony® II				ACCM			
<b>Power Management</b>	Amplify™ Compatible Gateway not included			No	Amplify™ Compatible				Symphony® II				No		
<b>Enclosure Type</b>	3R														
<b>Enclosure Material</b>	Steel														
<b>SED Rated</b>	Yes except Canada			No	Yes except Canada							No			
<b>Utility Breaker (A)</b>	100	150	200	N/A	100	150	200	100	150	200	225	No			
<b>Load Transition Type (Automatic)</b>	Open transition														
<b>UL Listing</b>	1008											1008, 414, 1008M		1008	
<b>Withstand Rating (RMS Symmetrical Amps)</b>	10,000	22,000	5,000 / 22,000 (with breakers)	10,000	22,000	10,000	25,000	22,000	5,000						
<b>Lug Range</b>	<b>Utility</b>	#6 - 1/0	2AWG - 300MCM	14AWG - 1/0	#6 - 1/0	2AWG - 300MCM	6AWG - 1/0	2AWG - 300MCM	N/A	14AWG - 1/0 AWG	14AWG - 6 AWG				
	<b>Generator</b>	14AWG - 1/0	6AWG - 250MCM	14AWG - 1/0	#14 - 1/0	6AWG - 250MCM	14AWG - 1/0	6AWG - 250MCM	6AWG - 250MCM	14AWG - 1/0 AWG	14AWG - 6 AWG				
	<b>Load</b>	14AWG - 1/0	6AWG - 250MCM	14AWG - 1/0	#14 - 1/0	6AWG - 250MCM	14AWG - 1/0	6AWG - 250MCM	N/A	N/A	14AWG - 1/0 AWG	14AWG - 6 AWG			
<b>Enclosure Size (L x W x D, Ins)</b>	20 x 14.5 x 7	30 x 14.5 x 7	24 x 14 x 6	20 x 14.5 x 7	30 x 14.5 x 7	24 x 14 x 6	30 x 16 x 7	34 x 24 x 7	27.5 x 11 x 6	27.75 x 11 x 6	16 x 12 x 6	21.2 x 14.5 x 5.4			
<b>Wire-Whip</b>	No			Available	No				Yes			No			
<b>Limited Warranty* (Years)</b>	5					6					5				